

AMENDMENTS TO THE CLAIMS

Following is a listing of all claims in the present application, which listing supersedes all previously presented claims:

Listing of the Claims:

Claims 1-8. (Canceled)

9. (Currently Amended) A sensing apparatus, comprising:

a fluxgate including

a driving coil for exciting a magnetic substance core with a current,

first and second current amplifiers for applying the current to first and second ends of the driving coil,

a pulse generator for generating a pulse to turn on/off the first and second current amplifiers, and

a pulse controller for outputting a control signal allowing the pulse to be applied to the first and second current amplifiers, the pulse controller outputting the control signal at a start of a sensing cycle, the fluxgate generating an analog signal due to the excited magnetic substance; [[and]] an A/D converter for converting the analog signal from the fluxgate into a digital signal, wherein the pulse controller stops outputting the control signal before an end of a cycle of the sensing apparatus when the A/D converter outputs the digital signal to the pulse controller; and

a logical gate for logical-operating the pulse from the pulse generator with the control signal from the pulse controller and for outputting the logical-operated signal to the first and second current amplifiers.

10. (Previously Presented) A sensing apparatus comprising:
- a fluxgate including
    - a driving coil for exciting a magnetic substance core with a current,
    - first and second current amplifiers for applying the current to first and second ends of the driving coil,
    - a pulse generator for generating a pulse to turn on/off the first and second current amplifiers,
    - a pulse controller for outputting a control signal allowing the pulse to be applied to the first and second current amplifiers, the pulse controller outputting the control signal at a start of a sensing cycle, the fluxgate generating an analog signal due to the excited magnetic substance;
    - an A/D converter for converting the analog signal from the fluxgate into a digital signal, wherein the pulse controller stops outputting the control signal when the A/D converter outputs the digital signal to the pulse controller; and
    - an AND gate for logical AND-ing the pulse from the pulse generator with the control signal from the pulse controller and for outputting an output signal to the first and second current amplifiers in accordance with the logical AND-ing.
11. (Previously Presented) The sensing apparatus as claimed in claim 10, wherein the pulse controller outputs a high level signal during conversion of the analog signal from the fluxgate, and the pulse controller outputs a low level signal when the conversion of the analog signal into the digital signal by the A/D converter is complete and the A/D converter outputs the digital signal to the pulse controller.

12. (Previously Presented) The sensing apparatus as claimed in claim 11, wherein the pulse controller outputs the low level signal a predetermined time period after the conversion of the analog signal into the digital signal is complete and the A/D converter outputs the digital signal to the pulse controller.

13. (Canceled).

14. (Currently Amended) A control method of a sensing apparatus having a driving coil for exciting a magnetic substance core with a current; first and second current amplifiers for applying current to first and second ends of the driving coil, respectively; a fluxgate with a pulse generator for generating a pulse to turn on/off the first and second current amplifiers; an A/D converter for converting an analog signal from the fluxgate into a digital signal; and a pulse controller for outputting a control signal for controlling the pulse generator, the control method comprising:

a) driving the pulse generator when the fluxgate initiates a drive and outputting a first control signal in order for the pulse generated from the pulse generator to be applied to the first and second current amplifiers; [[and]]

b) outputting a second control signal in order for the pulse generated from the pulse generator not to be applied to the first and second current amplifiers when the conversion of the analog signal into the digital signal by the A/D converter is complete before an end of a cycle of the sensing apparatus and the A/D converter outputs the digital signal to the pulse controller; and

c) logical-operating the pulse from the pulse generator with the control signal from the pulse controller and outputting the logical operated signal to the first and second current amplifiers.

15. (Previously Presented) A control method of a sensing apparatus having a driving coil for exciting a magnetic substance core with a current; first and second current amplifiers for applying current to first and second ends of the driving coil, respectively; a fluxgate with a pulse generator for generating a pulse to turn on/off the first and second current amplifiers; an A/D converter for converting an analog signal from the fluxgate into a digital signal; and a pulse controller for outputting a control signal for controlling the pulse generator, the control method comprising:

a) driving the pulse generator when the fluxgate initiates a drive and outputting a first control signal in order for the pulse generated from the pulse generator to be applied to the first and second current amplifiers;

b) outputting a second control signal in order for the pulse generated from the pulse generator not to be applied to the first and second current amplifiers when the conversion of the analog signal into the digital signal by the A/D converter is complete and the A/D converter outputs the digital signal to the pulse controller; and

logical AND-ing the pulse from the pulse generator with the control signal from the pulse controller and outputting an output signal to the first and second current amplifiers in accordance with the logical AND-ing.

16. (Previously Presented) The control method as claimed in claim 15, wherein in a) the pulse controller outputs a high level signal as the first control signal, and in b) the pulse controller outputs a low level signal as the second control signal.